



DESCRIPTION
The ASO is an analogue output module that is designed to convert 1 x 0-10 Volt input signal to 2, 3 or 4 x 0-10 Volt outputs operating in sequence. The output slopes can be set to overlap each other by up to 2 Volts by the adjustment of VR2. There is also an output variable delay timer which is set on VR1 (0 to 5 mins.)
FEATURES
* Microprocessor Based.
* 24 Volt AC/DC Supply.
* 1 Input signal to control in sequence up to 4 outputs.
* Output slopes can be overlapped by up to 2 Volts.
* Output signals can be operated with a variable time delay.
* DIN Rail mounting.

SPECIFICATION	
Input:	1 x 0-10 Volt
Output:	2, 3 or 4 x 0-10 Volt
Power Supply:	24 Volts AC or DC (± 15%)
Power Consumption:	25mA(max)
Terminals:	Max. cable size 1.0mm
Operating Temperature:	0 to +50°C
Dimensions:	85mm High 80mm Wide 45mm Deep
Mounting:	DIN Rail
Order Code:	ASO